

INSTALLATION INSTRUCTIONS FOR POWER-SAVE 1200

LOCATIONS AND INFORMATION:

1. Prior to opening the meter base or breaker panel MAKE CERTAIN THE MAIN BREAKER IS IN THE OFF POSITION.
2. If there is not space at the meter base, or you prefer, the POWER-SAVE 1200 can be installed at the load center (breaker panel).
3. Many homes have multiple breaker panels and the POWER-SAVE 1200 can be installed on any breaker panel in the home, providing there is space for the dedicated two pole 20 amp breaker.
4. The POWER-SAVE 1200 is designed to condition “ALL” power consumed by inductive loads (electric motors) in the home regardless of installation location.
5. If there are no spaces available at the meter base or breaker panel, a sub panel can be installed for the additional two pole 20 amp breaker.
6. The POWER-SAVE 1200 “MUST” be installed on a dedicated two pole 20 amp breaker.
7. The POWER-SAVE 1200 unit is enclosed in a NEMA 3 box allowing it to be installed indoors or outdoors, but it “CAN NOT” be installed under water.

INSTALLATION INSTRUCTIONS:

1. Prior to opening the meter base or breaker panel MAKE CERTAIN THE MAIN BREAKER IS IN THE “OFF” POSITION.
2. The power should remain “OFF” until the entire installation is complete.
3. Install a two pole 20 amp breaker and secure the two red leads (wires) of the POWER-SAVE 1200 unit, one on each side of the breaker. Leave breaker in “OFF” position until power is restored.
4. Secure the green wire from the unit to the ground bar in the panel.
5. Remove “tabs” (knockouts) from cover allowing access to breaker after cover is reinstalled.
6. Reinstall the panel cover securely.
7. Turn power (main breaker) back on. Flip the two pole 20 amp breaker to “ON” and check that the indicator light is on. This will indicate that the unit is on.
8. If the light is “not” on turn off the main power, and check to make certain good contacts are made with the two red wires and the breaker, and the green wire and the ground bar. Install cover, turn power back on, and check light again.
9. If light remains off call your dealer or tech support at 800-955-2238.
10. If your unit is humming this is a sign that you are receiving high voltage that exceeds 110/220 volts, but will not damage the unit.

WARRANTY: The POWER-SAVE 1200 has a five year warranty from date of installation. If you have a back-up generator, call support prior to installation, as some generators are not compatible with the POWER-SAVE 1200

WARNING: HAVE YOUR POWER-SAVE 1200 INSTALLED BY A LICENSED ELECTRICIAN. INSTALLING ELECTRICAL EQUIPMENT MAY RESULT IN SHOCK, SERIOUS INJURY, OR EVEN DEATH.